



MAX CONNECT BASIC

QUICK START GUIDE

Operator Default Password: 1012 1111

Location Default Password: 1013 1111

*Note that only the last four digits can be personalized, you must enter in the first four pin # (1012) and then your personalized last four pin # (1111, editable in page 5).

** if neither Operator or Location is logged in, the default login will be Attendant (ATD).

EGM Type (Admin page 3) - This is where you can edit each game # with their prospective software titles.

Operator Collection

Print Period – Prints the current period values **WITHOUT** clearing the periods.

Print Lifetime – Prints the MASTER In and Outs.

Collect Location – Prints the Period Collection Report **AND** clears current period values.

Print Collect – Prints the previous period that was collected by Collect Location.

Location Collection

Clear Shift – Clears the current period values.

Print Shift – Prints the current Shift In and Out **WITHOUT** clearing periods.

Print Lifetime – Prints the MASTER In and Outs.

Voucher History – View all printed Player Ticket Redemption.

Print List – Prints the Voucher History.

Reprint Voucher –Re-prints the selected voucher.

Drawer History – View log of all users who have had access to the cash drawer (Optional for Standard and Advanced MAX CONNECT).

*Note that the Operator and Location are separate, individual books that can be period-cleared at any time without affecting each other's period values.

Clear Master (Admin page 1) – Prints BEFORE Master Books Clear and AFTER Master Books Clear report.

Backing Up the POS Data to the Backup Thumb Drive

This function backups all MAX CONNECT settings, location info, and accounting data onto the Backup USB Thumb Drive.

1. Insert the Backup Thumb Drive.
2. In Admin page 1, press the BACKUP button.
 - a. Recommended after each Collect Location is performed.

Restoring Backup POS data from the Backup Thumb Drive

This function restores all MAX CONNECT settings, location info, and accounting data from the Backup USB Thumb Drive.

1. In Admin page 1, press the BACKUP button.
2. Press the EJECT button.
3. SHUTDOWN the POS.
 - a. IMPORTANT NOTE: DO NOT IMMEDIATELY TURN POWER OFF as soon as the screen goes blank because the MAX CONNECT files are still being backed up to the USB Thumb Drive!
 - b. Wait 15 Seconds OR until the green LED light on the Pi stays OFF.
4. After 15 seconds has passed OR the green LED light on the Pi had powered off, REMOVE the Backup Thumb Drive.
5. If needed, replace the MAX CONNECT Micro-SD card at this time.
6. Power on the POS WITHOUT the Backup Thumb Drive installed.
7. Install the Backup Thumb Drive when the POS prompts for the backup drive.
8. In Admin page 1, press the RESTORE button.
 - a. Data should have been restored from the previous saved backup files