

Genmega Switch Commerce Setup

Anything highlighted in blue is internet settings
Anything highlighted in green is dial-up settings

- To get into the menu press **Enter**, then **Clear**, then **Cancel**. The press **1, 2, 3**.
- **Operator Function**
- Enter password – **333333 enter**.
- **Settlement, add cassette 1** enter **10**, then press **Enter**
- **Cancel**.
- **Customer Setup, Change Message**
 - **Welcome message**
 - **Welcome to (Location Name)**
 - Press enter to save it once finished
 - **Receipt Header 1: Thank you**
 - **Receipt Header 2: Location Name**, press **ENTER**
 - **Receipt Header 3: Location Street Address**,
 - **Receipt Header 4: City, State, and Zip Code**. Press **ENTER**, then **Cancel**.
- **Optional Function**
 - **Location Name**
 - **Enter the Location Name. Press ENTER**
 - **Check Balance Option**
 - Check Balance
 - Enable, cancel
 - **EMV**
 - **Enable: EMV**
 - **Make sure all AID's are Enabled**
- **Surcharge mode**
 - **Owner**
 - Enter company who owns machine, press **ENTER**,
 - **Surcharge Option**
 - **Balance Fee Notice: Enabled then Cancel twice**.
- **Change Processor**
 - **Communication**
 - **SSL Pass through (Internet)**
 - **Modem (Dial Up)**
 - Message format
 - Standard 3



- **SSL Data Format**
 - **7 Bits Even Parity**

- **Standard 3 Option**
 - **Enable:** Status Monitoring
 - **Enable:** Communication Header
 - **Enable: TCIP CRC**

- **DCC Tran Option**
 - DCC Transaction, **Enable** (Only if the machine is on Internet or OptConnect). **Cancel back to Operator Function.**
- **System Setup**
 - **Set Clock, Date & Time**, adjust accordingly using the clear key to erase current numbers, the after entering new info press **Enter** to go to the next change to be made. When finished all changes press **Cancel**.

- **Change Password,**
 - **Passwords must be change. Do not make any 2 passwords the same.**
 - **Master, change to whatever password you choose.**
 - **Service 1, Change to 212121.**
 - **Service 2, Change to 313131.**
 - **Service 3, Change to 414141.**
 - **Operator, Change to 121212.**

- **Device Setup**
 - ATM TCPIP SETUP
 - **TCPIP Mode-DHCP**
 - Push Apply Button to save. **Cancel back to Operator Function.**
- **Host Setup**
 - **Remote Monitor**
 - **RMS En/Disable**, then Disable by pressing **En/Disable**.

 - **Host IP Address**
 - **Host Address 1: ATM1. SWITCHCOMMERCE.NET**
 - **Host Address 2: ATM2. SWITCHCOMMERCE.NET**
 - **Host Port 1&2: 1440**
 - **Configuration. Scheduled**

- **Host Phone**



- Host Phone 1: 18555721978
- Host Phone 2: 18555721979
- **Terminal Number**
 - enter the Terminal ID, press **ENTER**
- **Routing ID: 123SC101 press ENTER**
- **Key Management, Yes**, enter password **000000**, for both passwords.
- **Key Mode**, press 3 times to change to **TDES**. (**Very important that it read only TDES**).
- **Change Password**,
Password 1 enters **104620**, confirm by re-entering, then enter
Password 2, 264010, confirm by re-entering.
- **Edit Key, Master Key Part A**
- **Enter Key Index, 01 ENTER**
- Enter 1st set of keys. Each line must be entered twice.
- When done entering 1st set verify the Check Digit and press **Enter**.
- **Master Key Part B**
- **Enter Key Index, 01 ENTER**
- Enter 2nd set of keys. Each line must be entered twice.
- When done entering 2nd set verify the Check Digit and press **Enter**.
- Press **Cancel** 4 times.
- At this point the machine will call the host.
- Press **Enter, Clear, Cancel, 1,2,3**
- Enter Master password.
- **Report**
- **Error Summary. Press Clear**
- **Print All Setup**
 - **Put a copy in the top of ATM.**
- **Cancel** twice.